

DS-PR1-60V



- Supports separate radar web client configuration operation
- Supports to obtain target information such as the distance, direction, and angle
- Supports target positioning, tracking display and camera linkage
- Supports intrusion detection and cross-line alarm
- Supports multi-channel radars and multi-channel cameras linkage in same or different location
- Supports multi-target locking, multi-camera tracks multi-target
- Supports video linkage functions of multi-target: automatic switching and mandatory switching
- Selectable scene modes, configurable sensitivity
- Can filter out false alarms caused by trees or animals



▪ Specification

Detection performance	
Velocity measurement accuracy	± 0.55 m/s
Velocity range	- 8.7 to 8.7 m/s
Range measurement accuracy	± 5 m
Radar transmit power	≤20 dBm
Date fresh rate	6 frames / s
Detection angle	100°
Detection range	60 m
Microwave frequency	24.05 ~ 24.25GHz
Max. Target number	32
Software features	
Schedule	Auto Arm/Disarm Schedule
Configuration tools	Web / iVMS-4200
Firmware update tools	Web / iVMS-4200
Hardware features	
Serial port	RS232
Tamper-Proof	Tampering alarm
Network interface	1 RJ45 10M/100M/1000M self-adaptive, PoE
Electrical characteristics	
Power supply	Standard PoE / 12VDC
Power interface	802.3at standard PoE or 12VDC
Operation humidity	10% to 90%
Operation temperature	-40°C to 65°C
Power consumption	16 W
Wireless transmission	
RF modulation	FMCW
Display	
Indicator	Dual-color LED
General	
IK rate	IK09
IP rate	IP67
Installation method	Multiple installations with different brackets
Installation height	1.2 - 4m (Recommend Height: 2.5m)
Dimension(WxHxD)	206 mm × 228 mm × 61 mm (8.11" × 8.98" × 2.40")
Anti-corrosion	NEMA 4X
Application scenario	Outdoor
Shell material	PC+ABS
Color	White
Bracket	Multiple brackets
Weight	1.84 kg (4.06 lb)
Device management	
Alarm output	4 Relay Outputs(NO/NC)
Zones	8






Relay output	4-ch current output: 0.5A 125 VAC/1 A 30 VDC
Report method	
Protocol	HTTP, DNS, NTP, TCP, UDP, DHCP, ARP, SSH

▪ **Available Model**

DS-PR1-60V

▪ **Accessory**

▪ **Optional**

DS-PRB-2200	DS-PRB-1120	DS-PRB-1200	DS-PRB-1310	DS-PRB-1110
Radar bracket	Radar bracket	Radar bracket	Radar bracket	Radar bracket
				

Distributed by

**HIKVISION®****Headquarters**

No.555 Qianmo Road, Binjiang District,
Hangzhou 310051, China
T +86-571-8807-5998
overseasbusiness@hikvision.com

Hikvision USA
T +1-909-895-0400
sales.usa@hikvision.com

Hikvision Australia
T +61-2-8599-4233
salesau@hikvision.com

Hikvision India
T +91-22-28469900
sales@pramahikvision.com

Hikvision Canada
T +1-866-200-6690
sales.canada@hikvision.com

Hikvision Thailand
T +662-275-9949
sales.thailand@hikvision.com

Hikvision Europe
T +31-23-5542770
sales.eu@hikvision.com

Hikvision Italy
T +39-0438-6902
info.it@hikvision.com

Hikvision Brazil
T +55 11 3318-0050
Latam.support@hikvision.com

Hikvision Turkey
T +90 (216)521 7070- 7074
sales.tr@hikvision.com

Hikvision Malaysia
T +601-7652-2413
sales.my@hikvision.com

Hikvision UK & Ireland
T +01628-902140
sales.uk@hikvision.com

Hikvision South Africa
Tel: +27 (10) 0351172
sale.africa@hikvision.com

Hikvision France
T +33(0)1-85-330-450
info.fr@hikvision.com

Hikvision Kazakhstan
T +7-727-9730667
nikia.panfilov@hikvision.ru

Hikvision Vietnam
T +84-974270888
sales.vt@hikvision.com

Hikvision UAE
T +971-4-4432090
salesme@hikvision.com

Hikvision Singapore
T +65-6684-4718
sg@hikvision.com

Hikvision Spain
T +34-91-737-16-55
info.es@hikvision.com

Hikvision Tashkent
T +99-87-1238-9438
uzb@hikvision.ru

Hikvision Hong Kong
T +852-2151-1761
info.hk@hikvision.com

Hikvision Russia
T +7-495-669-67-99
saleru@hikvision.com

Hikvision Korea
T +82-(0)31-731-8817
sales.korea@hikvision.com

Hikvision Poland
T +48-22-460-01-50
info.pl@hikvision.com

Hikvision Indonesia
T +62-21-2933759
Sales.Indonesia@hikvision.com

Hikvision Colombia
sales.colombia@hikvision.com