

DVR/NVR VGA&HDMI&BNC Output Comparison Chart

DVR/NVR Firmware version:

DS-7604NI-SE/P, DS-7608NI-SE/8P: V2.3.7 Build 140122

DS-7200HWI-SH, DS-7300HWI-SH: V2.2.8 Build 130902

DS-9000&9600&7716: V3.0.2 Build 140126

Note:

Auxiliary here indicates Spot Output

Outputs		Model	NVR		DVR		
			8107	Netra	KY2013	Netra	
			DS-7604NI-SE/P	DS-7716NI-SP/16 DS-9600NI-ST/RT	DS-7200HWI-SH DS-7300HWI-SH	DS-9000HFI-ST	DS-9000HWI-ST
Video Output Interfaces		VGA, HDMI	VGA, HDMI, Main BNC	VGA, HDMI, Main BNC	VGA, HDMI, Main BNC, Auxiliary		
Connect VGA before DVR/NVR launch	VGA/HDMI	Menu	Menu display selectable between VGA and HDMI	Menu	Menu display selectable between VGA and HDMI	Menu	
	Main BNC	N/A	No menu, independent output, video display configurable	No menu, output same video display as VGA	No menu,Independent video outputs, video display configurable	No menu,Independent video outputs, video display configurable	
	Auxiliary		N/A	N/A	No menu,Multiple video outputs, video display configurable	No menu,Multiple video outputs, video display configurable	
Connect VGA after DVR/NVR launch	VGA/HDMI	Menu	No menu, independent output, video display configurable	No menu, output same video display as Main BNC	No menu, independent output, video display configurable	No menu, output same video display as Main BNC	
	Main BNC	N/A	Menu	Menu	Menu	Menu	
	Auxiliary		N/A	N/A	No menu, Multiple output, video display configurable	No menu, Multiple output, video display configurable	
Connect HDMI before DVR/NVR launch(Disconnect VGA)	HDMI	Menu	Menu, display selectable between VGA and HDMI	Menu	Menu, display selectable between VGA and HDMI	Menu	
	Main BNC	N/A	No menu, independent output, video display configurable	No menu, output same video display as HDMI	No menu, independent output, video display configurable	No menu, independent output, video display configurable	
	Auxiliary		N/A	N/A	No menu, Multiple output, video display configurable	No menu, Multiple output, video display configurable	
Connect HDMI after DVR/NVR launch(Disconnect VGA)	HDMI	Menu	No menu, independent output, video display configurable	No menu, output same video display as Main BNC	No menu, independent output, video display configurable	No menu, output same video display as Main BNC	
	Main BNC	N/A	Menu	Menu	Menu	Menu	
	Auxiliary		N/A	N/A	No menu, Multiple output, video display configurable	No menu, Multiple output, video display configurable	