

Title:	DS-PHA How to Upgrade Hybrid Security Control Panel by Browser	Version:	v1.0	Date:	03/23/2020
Product:	DS-PHA Series Hybrid Security Control Panel			Page:	1 of 4

Preparation

1. DS-PHA Series Hybrid Security Control Panel
2. iVMS-4200 or IE explorer
3. Newest firmware file


DS-PHA How to Upgrade Hybrid Security Control Panel by Browser

For Hybrid Panel, the difference user have different management permissions.

Admin is like master manager, it can Enable permission for installer and manufacturer account. So we can use **installer account or manufacturer account** to upgrade firmware.

Way 1: Use Installer Account Upgrade:

1. Login admin user.
 - 1) User Management---User---installer
 - 2) Enable installer user
 - 3) Click Operation




The screenshot shows the Hikvision web interface for User Management. The left sidebar contains a menu with 'User' highlighted. The main area displays a table of users with columns for No., User Name, User Type, Enable User, and Operation. The 'installer' user is selected, and its 'Enable User' toggle is turned on. A 'Save' button is at the bottom, and an 'Exit' button is in the top right corner.

No.	User Name	User Type	Enable User	Operation
1	admin	Administrator	<input type="checkbox"/>	
2	installer	Installer	<input checked="" type="checkbox"/>	
3	manufacturer	Manufacturer	<input type="checkbox"/>	

Title:	DS-PHA How to Upgrade Hybrid Security Control Panel by Browser	Version:	v1.0	Date:	03/23/2020
Product:	DS-PHA Series Hybrid Security Control Panel			Page:	2 of 4

4) Enable Remote Upgrade Permission



5) Click save

6) Click Exit

2. Login Installer user.

1) Login installer user

Account: **installer**


Default Password: **installer12345**

2) Click Login



Title:	DS-PHA How to Upgrade Hybrid Security Control Panel by Browser	Version:	v1.0	Date:	03/23/2020
Product:	DS-PHA Series Hybrid Security Control Panel			Page:	3 of 4

- 3) Select **System---System Maintenance---Upgrade and Maintenance**
- 4) View upgrade File and Click Upgrade




Way 2: Use Manufacturer Account Upgrade:

1. Login admin user.

- 1) **User Management---User---manufacturer**
- 2) Enable **manufacturer** user
- 3) Click save
- 4) Click Exit

Title:	DS-PHA How to Upgrade Hybrid Security Control Panel by Browser	Version:	v1.0	Date:	03/23/2020
Product:	DS-PHA Series Hybrid Security Control Panel			Page:	4 of 4



2. Login manufacturer user.

1) Login manufacturer user

Account: **manufacturer**


Default Password: **hik12345**

2) Click Login



Title:	DS-PHA How to Upgrade Hybrid Security Control Panel by Browser	Version:	v1.0	Date:	03/23/2020
Product:	DS-PHA Series Hybrid Security Control Panel			Page:	5 of 4

- 3) Select **System---System Maintenance---Upgrade and Maintenance**
- 4) View upgrade File and Click Upgrade



Hybrid Panel Corresponding Firmware

Firmware	Model
HIA_HYBRID_H1_ML_STD_V1.1.0_build200224	DS-PHA20-P
HIA_HYBRID_H1_ML_STD_V1.1.0_build200224	DS-PHA20-M
HIA_HYBRID_H1_ML_STD_V1.1.0_build200224	DS-PHA20-B
HIA_HYBRID_H1_ML_STD_V1.1.0_build200224	DS-PHA64-M
HIA_HYBRID_H1_ML_STD_V1.1.0_build200224	DS-PHA64-B
HIA_HYBRID_H10_ML_STD_V1.1.0_build200224	DS-PHA20-W2P
HIA_HYBRID_H10_ML_STD_V1.1.0_build200224	DS-PHA20-W2M
HIA_HYBRID_H10_ML_STD_V1.1.0_build200224	DS-PHA64-W4M
HIA_HYBRID_H10_ML_STD_V1.1.0_build200224	DS-PHA20-W2B
HIA_HYBRID_H10_ML_STD_V1.1.0_build200224	DS-PHA64-W4B

First Choice for Security Professionals
HIKVISION Technical Support