

Title:	How to watch Smart Playback in NVR	Version:	v1.0	Date:	12/13/2018
Product:	Cameras, NVR			Page:	1 of 8

How to watch Smart Playback in NVR

Description

The smart playback function provides an easy way to get through the less effective information. When you select the smart playback mode, the system will analyze the video containing the motion or VCA information. It will mark it with **red color** and play it in **normal speed**, while the video without motion will be played in the **16-time speed** (the speed function can be configurable, -E/-Q is not supported). The smart playback rules and areas are configurable.

Note: This speed function is now supported by almost all -K/-I/-super I series NVR.

Preparation

To get the smart search result, the **Dual-VCA** must be enabled in NVR.

Steps:

- 1. Enter Configuration interface by Web.
- 2. Select Video/Audio on the top-left side and Display Info. on Stream.
- 3. Click Enable Dual-VCA and Save button.



Title:	How to watch Smart Playback in NVR	Version:	v1.0	Date:	12/13/2018
Product:	Cameras, NVR			Page:	2 of 8

MIKVISION	Live View Pla	ayback Picti	re Configuration		👤 admin	🚯 Help	E→ Logout
🖵 Local	Video Display Info	on Stream Channel-	rero				
System	Camera	[D31] Camera 01	\checkmark				
Network	Enable Dual-VCA	L .					
🚱 Video/Audio							
Image	🗎 Save						
Event							
Storage							
C Vehicle Detection							
CA VCA							
Human Body Capture							

How to configure Smart Event:

1) In Web (take Line Crossing Detection as example)

Steps:

- 1. Enter **Configuration** interface and select **Event** in the drop-down list on the top-left side.
- 2. Select **Smart Event** in the following menu.
- 3. Select a camera in the camera list.



4. Select Line Crossing Detection and click Enable Line Crossing Detection.



Title:	How to watch Smart Playback in NVR	Version:	v1.0	Date:	12/13/2018
Product:	Cameras, NVR			Page:	3 of 8



5. Click Draw Area and take the line in the needed area and click Save button.



2) In Local (take Line Crossing Detection as example)

Steps:

- 1. Enter System interface and select Event in the drop-down list on the top-left side.
- 2. Select **Smart Event** in the following menu.
- 3. Select a camera in the camera list.



Title:	How to watch Smart Playback in NVR	Version:	v1.0	Date:	12/13/2018
Product:	Cameras, NVR			Page:	4 of 8

N	VR 4.0			, C		∕≙		כ	S	ç				۲		r,		
6	General		Carr	iera	[D1] D16				•	Save VC/	A Picture						
2	User		Face	Detection	Line C	rossing	Intrusio	n Un	attended B	aObjec	t Remova	sl Sudden	Scene					
\oplus	Network	>																
	Event	\sim	E	nable Face.			×.			Se	insitivity	1	0		5 3			
	Normal Event		Armir	ng Schedule	Linka	age Action												
	Smart Event			Continu	lous	None											Edit	
\sim	Live View	>			0	2	4	6	8	10	12	14	16	18	20	22	24	
Ş	RS-232			Mon													1	
÷	Holiday			Tue													2	
	POS			Wed													3	
1	Hot Spare			Thu													4	
				Fri													5	
				Sat													6	
				Sun													7	

4. Select Line Crossing and click Enable Line Crossing Detection.

N	VR 4.0		Ŕ	Þ		Ð	۲Ţ		٢	B		
@ L	General User		Camera Face Detection	[D1] D16	Intrusion	Unattended Ba.	Save VCA	Picture Sudden Scene				
	Network	2										
Ĩ	Event	~	Enable Line C	rossing Detection	n							
	Normal Event		Area Settings	Arming Schedule	Linkage Action							
	Smart Event					- 18		Acerica Acea				
Q	Live View	2	10-10-00	10 100 10				Arming Area	1.5			
Ş	RS-232				-	-		Direction	A<->8		•	
崮	Holiday							Sensitivity	1		100 50	
	POS		-	-		-						
Ţ	Hot Spare				- A	DIE	1					
			Draw Area	Clear	Max, Size	Min. Size						

5. Click **Draw Area** and take the line in the needed area and click **Apply** button.



Title:	How to watch Smart Playback in NVR	Version:	v1.0	Date:	12/13/2018
Product:	Cameras, NVR			Page:	5 of 8



How to use Smart detection in playback:

1) In Web (take Line Crossing Detection as example)

Steps:

- 1. Enter **Playback** interface, select **the camera** in the drop-down list on the top-left side and **the date** in the right side.
- 2. Select \square -> $\stackrel{\scriptstyle <}{\times}$ in the left bottom
- 3. Draw two points in the wanted area.



© Hangzhou Hikvision Digital Technology Co.,Ltd. All Rights Reserved. No.555 Qianmo Road, Binjiang District, Hangzhou 310052, China • Tel: +86-571-8807-5998 • Fax: +1 909-595-0788 E-Mail: <u>support@hikvision.com</u> • <u>www.hikvision.com</u>



Title:	How to watch Smart Playback in NVR	Version:	v1.0	Date:	12/13/2018
Product:	Cameras, NVR			Page:	6 of 8

2) In Local (take Line Crossing Detection as example)

Steps:

- 1. Enter Playback interface, select the camera and the date in the drop-down list on the top-left side.
- 2. Select **Smart** button in the bottom.

N	/R 4.0 🔬	2 💽		R []		(ES.	88	🤐 🚑 C
Chann	nel 🗸 🗸						A.L	so on the section of	and a strength of the
	Q)	10-19	-2018 11				ALCONO DE LA		Carrier and
Max. 0	Cam Min. Cam								Construction of the local division of the lo
	outside						In the second second		International Property in which the
	IPCamera 02			EIIIIIIIIII			and for starts		TA IN CONTRACTOR OF A DESCRIPTION OF A DESC
	IPCamera 03			aption of the Albertonia	a state of the sta		ana		
	IPCamera 04				De Martin	Northern Land	And I ADDRESS OF THE OWNER OF THE	AND THE REAL PROPERTY AND INCOMENDATION OF THE PARTY OF T	SHUD - CONTRACTOR
	IPCamera 05	Contraction of the second s	In Manuel		Transfer Alle		Che in The		
	IPCamera 06		A DIT TO A DIT A	and the second second			ALL SALES	and the second s	- Partier 1-
	IPCamera 07	199 199 1994			and the second sec				
	IPCamera 08		POST	at the					
Time					the second second	-			Contraction of the second
<	2018 Oct >	and the second sec		The set	and a state of the	Vielen al			
SM	TWTFS	- Internet the back of	and the second second	States -	-				
78	9 10 11 12 13	A DECEMBER OF THE OWNER	and and the Party	State of the state	The second se				
14 15	16 17 18 19 20					- Clip-	-	outsid	e
21 22	23 24 25 26 27	- States	-					The main and the second second	an and an area
28 29	30 31	Normal	Smart Cust	om Tag 🤍	2018-10-19 16	5:42:24		1h	•••••••
		16:15	16:20 16:25	ielai ielai	16:40	16:45 16:	50 16:55	17:00 1	7 05 17 10
C	Custorn Search	E HI X	E		I	44 ×1	ÞÞ ■Nor ■	Smart=DST	E 🕯 🗆 💱

3. Select in the middle of the screen.



4. Draw two points in the wanted area.



Title:	How to watch Smart Playback in NVR	Version:	v1.0	Date:	12/13/2018
Product:	Cameras, NVR			Page:	7 of 8



How to watch Smart Play back in speed:

Steps:

- 1. Enter **Playback** interface, select **the camera** and **the date** in the drop-down list on the top-left side.
- 2. Select **Smart** button in the bottom.
- 3. Click 🔲 in the bottom of the screen.
- 4. Choose the wanted speed.

NVR 4.0		si (D		\odot			63	Ş	
Channel	\sim									
	Q									
Max. Camera for Min. Camera	for									
D16										
2955										
□ 4A										
Sophia Test										
IPCamera 05										
IPCamera 06										
IPCamera 07										
IPCamera 08										
Time	~									
	~									
2018 540	_									
SMTWTF	s									
	1		Play	y Strategy						
2 3 4 5 6 7	8									
9 10 11 12 13 14	15			Do not Play N	ormal Videos	Y				
16 17 18 19 20 2	22			Normal Video			0	X8		
23 24 25 26 27 21	29	Normal Smart	Cus	Play Speed of	Smart/Custon	·		X1	1	
30 31	22'20	23 35	23.40			C	ж	Cancel	00-10 00-15 00	20 00'25 00'30
Custom Search			E3		⊲	⊳ ⊲	(II) 🛛	X1 ÞÞ	Normal	Smart 🖹 🔯 💷 💱



Title:	How to watch Smart Playback in NVR	Version:	v1.0	Date:	12/13/2018
Product:	Cameras, NVR			Page:	8 of 8

First Choice for Security Professionals *HIKVISION* Technical Support