

## DS-PEA4L-7 Panic Alarm Master Station

DS-PEA4L-7 panic alarm master station is designed with 7 inch HD touch screen. It supports live view, two-way audio and it works with emergency alarm devices.



### Key Features

- Tempered glass panel and aluminum alloy bracket
- Video intercom among the pole panic alarm station, the panic alarm station, the box panic alarm station, and the panic alarm master station
- Live view of linked network cameras
- Visualized alarm information
- Hardware noise reduction and echo cancellation
- Hands-free calls and calling by handset
- Receives and displays real-time alarm information of network cameras
- Wall mounting and base mounting with multiple angles
- Supports two-way audio, listening, monitoring, packet broadcasting, and speed dial
- 7-inch touch screen and soft key



## Specifications

Model		DS-PEA4L-7
System parameters	Processor	High-Performance Embedded SOC Processor
	Operation system	Embedded Linux Operation System
Display Screen Parameters	Screen	7-inch Capacitive Touch Screen; Color; TFT LCD
	Resolution	1024*600
	Operation type	Touch Screen; Soft Key; Button
Audio parameters	Audio input	Built-in Microphone, Handset
	Audio output	Built-in Loudspeaker, Handset
	Audio compression standard	G.711 U/64Kbps, G.726 /16Kbps
Network parameters	Network protocol	TCP/IP, RTSP, SNMP, HIK-SIP
	Ethernet	10 M/100 M/1000 M Self-adaptive Ethernet port
Device interfaces	Network interface	1 RJ45 10M/100M/1000 M Self-adaptive Ethernet Ports
General	Power supply	12V DC
	Power consumption	≤ 10 W
	Working temperature	-10° C to +50° C (14° F to 122° F)
	Working humidity	10% to 90%
	Dimensions	436 mm × 215 mm × 67 mm (17.17" × 8.46" × 2.64")

## Available Models

DS-PEA4L-7

Adapter (From 220VAC to 12 VDC)

Distributed by



## HIKVISION®

### Headquarters

No.555 Qianmo Road, Binjiang District,  
Hangzhou 310051, China  
T +86-571-8807-5998  
overseasbusiness@hikvision.com

**Hikvision USA**  
T +1-909-895-0400  
sales.usa@hikvision.com

**Hikvision Italy**  
T +39-0438-6902  
info.it@hikvision.com

**Hikvision Singapore**  
T +65-6684-4718  
sg@hikvision.com

**Hikvision Africa**  
T +27 (0) 0351172  
sale.africa@hikvision.com

**Hikvision Europe**  
T +31-23-55-42-770  
info.eu@hikvision.com

**Hikvision France**  
T +33(0)1-85-330-450  
info.fr@hikvision.com

**Hikvision Oceania**  
T +61-2-8599-4233  
salesau@hikvision.com

**Hikvision Hong Kong**  
T +852-2151-1761

**Hikvision Middle East**  
T +971-4-8816086  
salesme@hikvision.com

**Hikvision Spain**  
T +34-91-737-16-55  
info.es@hikvision.com

**Hikvision Canada**  
T +1-909-895-0400  
sales.usa@hikvision.com

**Hikvision Russia**  
T +7-495-669-67-99  
saleru@hikvision.com

**Hikvision Poland**  
T +48-22-460-01-50  
poland@hikvision.com

**Hikvision Korea**  
T +82-31-731-8841  
sales.korea@hikvision.com

**Hikvision India**  
T +91-22-28469900  
sales@pramahikvision.com

**Hikvision UK**  
T +01628-902140  
support.uk@hikvision.com

**Hikvision Brazil**  
T +55 11 3318-0050  
Latam.support@hikvision.com